

Bernalillo Co. Amateur Radio Emergency Service Net Guide

At 6:50 pm hours monitor your favorite URFMS repeater for activity. If no activity or if you can break into the activity before 6:55 pm say "***This is (your call) linking 146.90, 146.940, and 146.960***". Link 146.900 (Kirtland AFB), 146.940 (Mt. Taylor), 146.960 (Capilla Pk.).

Listen for activity and during a break say "***This is (your call) the net control for the Bernalillo Co. Amateur Radio Emergency Service Net. This net will begin at 7 pm, in approximately 5 minutes from now on these frequencies. I have linked up 146.90 to 146.940 and 146.960.***"

At 7 pm say "***This is (your call), the Bernalillo Co. ARES net control calling all ARES members and any other interested amateurs. This net meets each Thursday at 7 pm for the passing ARES information or instructions. If anyone needs to use these frequencies for priority traffic, please feel free to call now or anytime during the net.*** Pause a little while to see if anyone has any traffic.

"Nothing heard, we will proceed with the call for the ARES officials at this time".

Section Manager	Don	W5FHA
District Emergency Coordinator	Mike	K5MJE
Emergency Coordinator for SEARCH & RESCUE	Ed	N5LI
Emergency Coordinator for the County EOC	Chris	K5NRL
Emergency Coordinator for the BCSO Mobile Command Post	John	WB6QKF
Emergency Coordinator of the Red Cross	Ralph	W5EEI
Emergency Coordinator for Special Events	Ed	N5LI

After the officials, proceed with the general check-ins. Begin the check-in process as described below. Pause after calling, log each check-in, and note those with traffic.

First, call the members that are on the frequent check-in list. When that list is completed, continue with the general call for check-ins. After a group has checked-in, repeat each call and pause for possible corrections or break-ins. Pause occasionally to say your call and that you are the ARES net control.

"We will now proceed with general check-ins. Please state whether you have traffic or comments".
"All those with their suffixes beginning with the letters Alpha through Golf, please call now".
"All those with their suffixes beginning with the letters Hotel through Romeo, please call now".
"All those with their suffixes beginning with the letters Sierra through Zulu, please call now".
"A final call Alpha through Zulu, please call now".

Call back each check-in with indications of having traffic or comments.

"Is there anyone desiring to talk to another station?"

"Is there any further business for the net tonight?"

"Nothing more heard, the Bernalillo Co. ARES wishes to thank the Upper Rio FM Society for the use of their repeaters. Thank you all for checking in tonight. The ARES net is secure as of (time). This is (your call) unlinking now. Unlink each repeater you linked in, returning the system to the state in which you found it.